



Money Controls

Money Controls Pty Ltd A.B.N. 16 077 572 760

Unit 1, 2 Morton St Parramatta NSW 2150 Australia
Tel: +61 (0) 2 9683 5033 Fax: +61 (0) 2 9683 5055

SR3 TECHNICAL BULLETIN No: 1 DISABLING ALARM FUNCTION

It has been reported that some vending machines are being free vended by sticking an object up the coin reject chute. The SR3 is detecting the object being inserted into the validator and is outputting an Alarm signal which is a combination of all of the Accept lines turned on together.

On some machines this Alarm signal is seen as a valid coin being accepted and a credit is issued. To disable the Alarm signal on these machines you will need to do the following:

Switch off the power to the SR3.



SW1	SW2	SW3	SW4	SW5	SW6
OFF	OFF	OFF	ON	OFF	OFF

Switch on the power to the SR3.

Press the reject lever within 20 seconds. **(Mode 10 can be accessed at any time).**

The LED will flash GREEN.

Switch off the power to the SR3.

Set ALL the DIL switches to the OFF position.

Switch on the power to the SR3.

The alarm is now OFF.

In future the Alarm function will be disabled by default on all SR3 unless specified.

For further information on this technical bulletin or any other technical issues please contact Mr. Glenn Wlikinson, Technical Services Manager, on the above contact numbers or E-mail glenn@moneycontrols.com.au